

©2013

EPROM - DATA

©2013

This web site was designed to be best viewed in 1280 x 1024 or wider using **MOZILLA's FIREFOX**
An excellent variety of free to read DATA SHEETS on various EPROMS

[2532](#), [2708](#), [2716](#), [2732](#), [2764](#), [27128](#), [27C128](#), [27256](#), [27C256](#),
[27512](#), [27C512](#), [27C1000](#), [271001](#), [272001](#), [274001](#) EPROM series
EPROM and CMOS EPROM UV Eraseable EPROM and OTP-EPROM

This page was updated August 11th 2011

[←INDEX - MAIN PAGE](#)

[←Go Back](#)

[BOTTOM ↓](#)

[NEXT →](#)

Email us :sales@unitechelectronics.com

Memory: EPROM and CMOS EPROM UV Eraseable

2532

4K x 8 bits EPROM. Requires -5V, +5V and +25V.

A7	1	24	VCC
A6	2	23	A8
A5	3	22	A9
A4	4	21	VPP
A3	5	20	PD/PGM
A2	6	19	A10
A1	7	18	A11
A0	8	17	D7
D0	9	16	D6
D1	10	15	D5
D2	11	14	D4
GND	12	13	D3

[TOP ↑](#)

2708

1k x 8 bits EPROM. Requires -5, +5 and +12V.

A7	1	24	VCC
A6	2	23	A8
A5	3	22	A9
A4	4	21	VEE
A3	5	20	/CE
A2	6	19	VDD
A1	7	18	PGM
A0	8	17	D7
D0	9	16	D6
D1	10	15	D5
D2	11	14	D4
GND	12	13	D3

[TOP ↑](#)

2716

2k x 8 bits EPROM.

A7	1	24	VCC
A6	2	23	A8
A5	3	22	A9
A4	4	21	VPP
A3	5	20	/OE
A2	6	19	VDD
A1	7	18	/CE
A0	8	17	D7
D0	9	16	D6
D1	10	15	D5
D2	11	14	D4
GND	12	13	D3

TOP ↑

2732

4k x 8 bits EPROM.

A7	1	24	VCC
A6	2	23	A8
A5	3	22	A9
A4	4	21	A11
A3	5	20	/OE VPP
A2	6	19	A10
A1	7	18	/CE
A0	8	17	D7
D0	9	16	D6
D1	10	15	D5
D2	11	14	D4
GND	12	13	D3

TOP ↑

2764

8k x 8 bits EPROM. Available in -300 and -600 mil pkgs.

VPP	1	28	VCC
A12	2	27	/PGM
A7	3	26	NC
A6	4	25	A8
A5	5	24	A9
A4	6	23	A11
A3	7	22	/OE
A2	8	21	A10
A1	9	20	/CE
A0	10	19	D7
D0	11	18	D6
D1	12	17	D5
D2	13	16	D4
GND	14	15	D3

TOP ↑

27C64

8k x 8 bits CMOS EPROM. Available in -300 and -600 mil pkgs.

VPP	1	28	VCC
A12	2	27	/PGM
A7	3	26	NC
A6	4	25	A8
A5	5	24	A9
A4	6	23	A11
A3	7	22	/OE
A2	8	21	A10
A1	9	20	/CE
A0	10	19	D7
D0	11	18	D6
D1	12	17	D5
D2	13	16	D4
GND	14	15	D3

TOP ↑

27128

16k x 8 bits EPROM. Available in -300 and -600 mil pkgs.

VPP	1	28	VCC
A12	2	27	/PGM
A7	3	26	A13
A6	4	25	A8
A5	5	24	A9
A4	6	23	A11
A3	7	22	/OE
A2	8	21	A10
A1	9	20	/CE
A0	10	19	D7
D0	11	18	D6
D1	12	17	D5
D2	13	16	D4
GND	14	15	D3

TOP ↑

27C128

16k x 8 bits CMOS EPROM. Available in -300 and -600 mil pkgs.

VPP	1	28	VCC
A12	2	27	/PGM
A7	3	26	A13
A6	4	25	A8
A5	5	24	A9
A4	6	23	A11
A3	7	22	/OE
A2	8	21	A10
A1	9	20	/CE
A0	10	19	D7
D0	11	18	D6
D1	12	17	D5
D2	13	16	D4
GND	14	15	D3

TOP ↑

27256

32k x 8 bits EPROM. Available in -300 and -600 mil pkgs.

VPP	1	28	VCC
A12	2	27	A14
A7	3	26	A13
A6	4	25	A8
A5	5	24	A9
A4	6	23	A11
A3	7	22	/OE
A2	8	21	A10
A1	9	20	/CE
A0	10	19	D7
D0	11	18	D6
D1	12	17	D5
D2	13	16	D4
GND	14	15	D3

TOP ↑

27C256

32k x 8 bits CMOS EPROM. Available in -300 and -600 mil pkgs.

VPP	1	28	VCC
A12	2	27	A14
A7	3	26	A13
A6	4	25	A8
A5	5	24	A9
A4	6	23	A11
A3	7	22	/OE
A2	8	21	A10
A1	9	20	/CE
A0	10	19	D7
D0	11	18	D6
D1	12	17	D5
D2	13	16	D4
GND	14	15	D3

TOP ↑

27512

64k x 8 bits EPROM. Available in -300 and -600 mil packages.

A15	1	28	VCC
A12	2	27	A14
A7	3	26	A13
A6	4	25	A8
A5	5	24	A9
A4	6	23	A11
A3	7	22	/OE VPP
A2	8	21	A10
A1	9	20	/CE
A0	10	19	D7
D0	11	18	D6
D1	12	17	D5
D2	13	16	D4
GND	14	15	D3

TOP ↑

27C512

64k x 8 bits CMOS EPROM. Available in -300 and -600 mil packages.

A15	1	28	VCC
A12	2	27	A14
A7	3	26	A13
A6	4	25	A8
A5	5	24	A9
A4	6	23	A11
A3	7	22	/OE VPP
A2	8	21	A10
A1	9	20	/CE
A0	10	19	D7
D0	11	18	D6
D1	12	17	D5
D2	13	16	D4
GND	14	15	D3

TOP ↑

MX27C1000

1M-BIT [128K x 8] CMOS EPROM

VPP	1	32	VCC
A16	2	31	PGM
A15	3	30	NC
A12	4	29	A14
A7	5	28	A13
A6	6	27	A8
A5	7	26	A9
A4	8	25	A11
A3	9	24	OE
A2	10	23	A10
A1	11	22	CE
A0	12	21	Q7
Q0	13	20	Q6
Q1	14	19	Q5
Q2	15	18	Q4
GND	16	17	Q3

TOP ↑

271001

128k x 8 bits EPROM.

VPP	1	32	VCC
A16	2	31	/PGM
A15	3	30	NC
A12	4	29	A14
A7	5	28	A13
A6	6	27	A8
A5	7	26	A9
A4	8	25	A11
A3	9	24	/OE
A2	10	23	A10
A1	11	22	/CE
A0	12	21	D7
D0	13	20	D6
D1	14	19	D5
D2	15	18	D4
GND	16	17	D3

TOP ↑

271024

64k x 16 bits EPROM.

VPP	1	40	VCC
/CE	2	39	/PGM
D15	3	38	NC
D14	4	37	A15
D13	5	36	A14
D12	6	35	A13
D11	7	34	A12
D10	8	33	A11
D9	9	32	A10
D8	10	31	A9
GND	11	30	GND
D7	12	29	A8
D6	13	28	A7
D5	14	27	A6
D4	15	26	A5
D3	16	25	A4
D2	17	24	A3
D1	18	23	A2
D0	19	22	A1
/OE	20	21	A0

TOP ↑

272001

256k x 16 bits EPROM.

VPP	1	32	VCC
A16	2	31	/PGM
A15	3	30	A17
A12	4	29	A14
A7	5	28	A13
A6	6	27	A8
A5	7	26	A9
A4	8	25	A11
A3	9	24	/OE
A2	10	23	A10
A1	11	22	/CE
A0	12	21	D7
D0	13	20	D6
D1	14	19	D5
D2	15	18	D4
GND	16	17	D3

TOP ↑

274001

512k x 16 bits EPROM.

VPP	1	32	VCC
A16	2	31	A18
A15	3	30	A17
A12	4	29	A14
A7	5	28	A13
A6	6	27	A8
A5	7	26	A9
A4	8	25	A11
A3	9	24	/OE
A2	10	23	A10
A1	11	22	/CE
A0	12	21	D7
D0	13	20	D6
D1	14	19	D5
D2	15	18	D4
GND	16	17	D3

" DISCLAIMER "

We believe the above information to be correct, however typographical errors can occur and it is for this very reason we provide the above information "as is" with "no Warranty" as to "correctness" nor to its "accuracy". Please, always check & verify with your "own" data books or via a "Google" search on the net.

E. & O. E.

sales@unitechelectronics.com

This website, its graphics concept and design and layout are Copyright © 1985 - 2011 to Unitech Electronics Pty. Ltd. Est. 1978. E. & E. O. We ship globally from our Sydney, Australia office

←INDEX -MAIN PAGE

←Go Back

TOP ↑

NEXT →